

### **For Primary Or Redundant Alarm Communications**

The 4GM3 includes the latest LTE technology for the best performance and longest life cycle. Compatible with 3G and LTE cellular networks. The 4GM3 is designed as a summary event communicator. Installation and activation of the 4GM3 is quick and easy using website, Installer app, or a live operator.

### **For Industrial Monitoring**

The 4GM3 easily adapts to non-security applications for remote monitoring of just about anything that your customers need to monitor. This is a great device for expanding your customer base and increasing recurring monthly revenue!

Popular remote monitoring applications include:

- Sewer Lift Stations
- Agriculture
- Generator Power
- Sports and Safety Lighting
- Mechanical Chillers and Freezers
- Industrial System Controls

### **Device Features**

- Primary or redundant alarm communications for residential or commercial security
- Supports virtually all security systems and multiple formats
- Power from the panel or separate 12V DC power supply (not included)
- Four inputs and two outputs

### **Ordering Options**

- 4GM3-V – LTE Universal Cellular Alarm Communicator with Antenna (Verizon)
- 4GM3-A – LTE Universal Cellular Alarm Communicator with Antenna (AT&T)



### **Features**

- Secure dealer website for activation, configuration, and management
- Flat-rate billing with no overage charges
- Programmable periodic test intervals
- Works with virtually any central station
- Works with Uplink Remote for smartphone control and end-user notifications
- Mobile activation and signal strength with Uplink Installer™
- Live technical and activation support, 8:00 a.m. to 8:00 p.m. EST, Monday through Friday



# Universal Device Alarm Communicator

4GM3  
Device

## Specifications

### INPUTS

- |             |   |
|-------------|---|
| Four Inputs | <ul style="list-style-type: none"> <li>• Input 1: Configurable to connect to siren/bell (distinguishes between burg/steady and fire/pulsed) or 12 volts.</li> <li>• Inputs 2-4: 12 volts</li> </ul> |
|-------------|---|

### OUTPUTS AND REPORTING

- |                 |   |
|-----------------|---|
| Central Station | <ul style="list-style-type: none"> <li>• Contact ID, SIA, Pulse 4/2 and Modem IIe/IIIa2</li> <li>• Internet or Dial-up</li> </ul> |
| Relay Outputs   | Two — configurable  |
| Testing         | Weekly or Daily   |
| Other Reporting | <ul style="list-style-type: none"> <li>• Low Voltage</li> <li>• Email alerts to customer or alarm company</li> </ul>              |
| Status LED      | <ul style="list-style-type: none"> <li>• Network</li> <li>• Service</li> <li>• Communications</li> </ul>                          |

### RADIO

- |                      |  |
|----------------------|--|
| LTE                  | Compatible with 3G and LTE Networks  |
| Cellular Frequencies | 850/1900 MHz   |
| Transmit Power       | Maximum Allowable: <ul style="list-style-type: none"> <li>• 1.0W at 1900 MHz</li> <li>• 2.0W at 850 MHz</li> </ul> |

### DIMENSIONS

- |                      |                         |
|----------------------|-------------------------|
| Height, Width, Depth | 4.75 x 3.3 x 1.3 inches |
|----------------------|-------------------------|

### POWER SOURCE – NOT INCLUDED

- |                    |  |
|--------------------|--|
| Power Requirements | 12V DC<br>500 mA max on transmit<br>28mA standby |
|--------------------|--|

### OPTIONAL ACCESSORIES

- |  |
|--|
| Magnetic mount antenna with 9ft cable – part number -5304591                 |
| 8 inches tall high gain antenna with articulating joint – part number 530584 |
| 12-pin serial cable for panel direct connect – part number 5304576           |

• Document # DS-4GM3-1.0    • Copyright © 2021 Harding Instruments Co. Ltd.    • All Specifications are subject to change without notice    • Printed in Canada



9564 Yellowhead Trail NW    Tel 780.462.7100  
 Edmonton, Alberta, T5G 0W4    Fax 780.450.8396  
[sales@harding-tech.com](mailto:sales@harding-tech.com)    [www.harding-tech.com](http://www.harding-tech.com)



Represented by: